

# **LED Wash Zoom 36x12W RGBW Moving Head Lighting**



**Please carefully read the product description before use**

## **Maintenance**

1. Please keep the light in dryness and avoiding use in wet place.
2. Using intermittently can be extended the life.
3. Attention to clean the fan and lens usually in order to get the ventilating effects and lighting effects better.
4. Please do not wipe the crust using organic menstruum for avoid to damaged the product.

## **Statement**

The product has well capability and intact packing when leave factory, All of the user should comply with above warning item and manual ,any misuse cause of the

damages are not included in our guarantee, and also can't be responsible for any malfunction & problem owing to ignore the manual.

Please forgive that we will not be notice for technical change

### **Attention Item**

1. For guarantee the life of product, please don't put it on the wet place and not use it the place over 40 degree.
2. Please don't lay the product on the un-fixable or shakable place.
3. Ask for the professional to maintain the product in order to avoid the danger of get an electric shock.
4. Power supply should not be changed over +&-10% while the light is using, it will be decreased the life of lamp if the power is too high, but it will be influenced the luminosity if the power is too low.
5. After power off, if it is need used again, please cool down over 20 minuter.
6. Please look round the manual for ensure the product can be used normally.

### **DMX Channel Summary-16 Channels Mode**

Channel	Value	Features
CH1	0-255	Total dimming
CH2	0-255	Red Dimmer
CH3	0-255	Green Dimmer
CH4	0-255	Blue Dimmer
CH5	0-255	White Dimmer
CH6	0-255	Total light adjustment
CH7	0-255	X axis rotation
CH8	0-255	Y axis rotation
CH9	0-255	X-axis fine-tuning
CH10	0-255	Y axis fine-tuning
CH11	0-255	XY speed adjustment
CH12	0-255	focusing
CH13	0-255	Strobe
CH14	0-249	Self-propelled mode
	250-255	Voice control mode
CH15	0-255	CH16 speed adjustment
CH16	0-255	Alternate channel

## Display Control Instruction

Address	0-512	Address code adjustment
RunMode	DMX	14/18 channel selection (14 channels are virtual settings)
	Auto	Automatic mode 1-8
	Sound	Receive external sounds or vibrations, run built-in program effects
	Return	return
TestMode	Pan	X-axis motor adjustment
	Tilt	Y-axis motor regulation
	Focus	Focusing motor adjustment
	Red	Red Dimmer
	Green	Green Dimmer
	Blue	Blue Dimmer
	White	White Dimmer
	Return	return
Language	中文	Chinese
	English	English
	Return	return
Setup	IdCode	ID code adjustment
	PanReverse	on off
	TiltReverse	on off
	FaderDelay	on off
	SignalLink	on off
	CodeWheel	on off
	TempSwitchSet	on off
	TemperatureSet	50-120
	ScreenSaver	Mode 1, Mode 2, Off
	DisplayReverse	on off
	FactorySet	Factory settings
	RESET	Motor reset
	TouchCorrect	TouchCorrect
	PanOffset	0-255
	TiltOffset	0-255
Return	return	
SysInfo	**	**

## **Product Introduction**

- \* Power Supply:AC90--275V,50--60HZ
- \* Power consumption:720W
- \* Fixing lamp:LED Wash Zoom 36x12W RGBW Moving Head Lighting
- \* DMX-Control-channels:18 DMX Channels
- \* Shuttle:Flash rate:0--10HZ
- \* Dimmer:0-100% mechanic dimmer
- \* Long Lifespan LEDs(more than 60,000 hours)