

Remote Control



Technical Specification

*Feature:

- (1) Built-in many kinds of nice amazing effects
- (2) Four working modes: AUTO、Sound Flash、DMX512、Master/Slave
- (3) Under DMX mode, user can set light ON/OFF, output lens selection with adjustable speed, flash output lens selection with adjustable speed, spin direction with adjustable speed.

*LCD display with 4 digital button: Mode、UP、DOWN、ENTER

*Beam angle: 150 degrees

*Scanning system: stepper motor scanning

*DMX Channel: 7CH


*Net Weight: 1,1Kg

*Interface: 3 pins XLR jack for DMX or Maser-Slave linking

*Power Supply: Bi-Voltage 110V to 220V-250V, 50/60HZ, Power 15W

*Applicable Place: DJ、Bands、Bars、Pubs、Clubs、KTV、Family party、 etc.

LCD Digital Display



MENU: Function mode selection, such as DMX512 / master-slave, Automatic stroboscopic, voice-controlled stroboscopic, constant light, brightness adjustment
UP/DOWN: Previous or next, increase or decrease
ENTER: Confirm and save

Display menu:

DEFN	LIG1 (1R00 — 1R01)
	LIG2 (2R00 — 2R01)
	LIG3 (1G00 — 1G01)
	LIG4 (1B00 — 1B01)
	MOTO (1M00 — 1M99)
	UU (UU00 — UU99)
	RED (R000 — R099)
	GREE (G000 — G099)
	BLUE (B000 — B099)
	STRB (SH01 — SH99)
AUTO	PA01 — PA99
LED Gradual change	PJ01 — PJ99
AUTO Flash	PF00 — PF99
Laser AUTO	PC00 — PC99
LED AUTO	PL00 — PL99
DJ Sound	DJ00 — DJ99
LED DJ Sound	DE00 — DE99
DMX ADDRESS(CH11)	R001 — R512

DMX512 Channel

Mode(CH11)	Channel	Description
1	Special channel	000-030 NO
		031-070 AUTO
		071-110 LED Gradual change
		111-150 Flash AUTO
		151-190 DJ Sound
		191-230 LED DJ Sound
		231-255 NO
2	Red laser 1	000-255
3	Red laser 2	000-255
4	Green laser	000-255
5	Blue laser	000-255
6	Motor speed	000-255
7	UV	000-255
8	LED Red	000-255
9	LED Green	000-255
10	LED Blue	000-255
11	Flash	000-000 OFF
		001-004 ON
		005-029 Random flash
		030-255 Flash speed slow to fast