

LED Three Claws

Thanks for your choosing our products, please read the instruction carefully before using.

Technique Parameter:

Voltage: AC220V

Frequency: 50-60Hz

Power: 50W

LED: 72PCS, 5mm

Method of Dial Address Code:

ON	OFF	Function
	1.2.3.4.5.6.7.8.9.10	Auto Run
9	1.2.3.4.5.6.7.8.10	Sound Active(sensitivity can be adjusted)
10	1.2.3.4.5.6.7.8.9	DMX512,8CH

Master-Slave DMX Control:

Light Number	ON(address code)	OFF(address code)
Light 1	10	1.2.3.4.5.6.7.8.9
Light 2	5.10	1.2.3.4.6.7.8.9
Light 3	6.10	1.2.3.4.5.7.8.9.
Light 4	5.6.10	1.2.3.4.7.8.9.
Light 5	7.10	1.2.3.4.5.6.8.9
Light 6	5.7.10	1.2.3.4.6.8.9
Light 7	6.7.10	1.2.3.4.5.8.9
Light 8	5.6.7.10	1.2.3.4.8.9.
Light 9	8.10	1.2.3.4.5.6.7.9
Light 10	5.8.10	1.2.3.4.6.7.9
Light 11	6.8.10	1.2.3.4.5.7.9
Light 12	5.6.7.8.10	1.2.3.4.9

DMX Channel Function:

CH1: Control the position of pattern A

CH2: Control the position of pattern B

CH3: Control the position of pattern C

CH4: Control the speed of pattern runing

CH5: Control the different of pattern

CH6: Control the different of pattern

CH7: Control the different of pattern

CH8: Control the rotating speed of pattern

Note: There are three LED board in this light.

